

Orion-Tr DC-DC converters isolated

100 / 250 / 400 Watt



Orion-Tr 24/12-20 (240 W)



Orion-Tr 24/12-20 (240 W)

Remote on-off

The remote on-off eliminates the need for a high current switch in the input wiring. The remote on-off can be operated with a low power switch or by for example the engine run/stop switch (see manual).

All models are short circuit proof and can be paralleled to increase output current

An unlimited number of units can be connected in parallel.

High temperature protected

The output current will reduce at high ambient temperature.

IP43 protection

When installed with the screw terminals oriented downwards.

Screw terminals

No special tools needed for installation.

Input fuse (not replaceable)

On 12 V and 24 V input models only.

Adjustable output voltage

Not intended for battery charging. Please consider using an Orion-Tr Smart for battery charging.

Isolated converters 110 – 120 W	Orion-Tr 12/12-9 (110 W)	Orion-Tr 12/24-5 (120 W)	Orion-Tr 24/12-9 (110 W)	Orion-Tr 24/24-5 (120 W)	Orion-Tr 24/48-2,5 (120 W)	Orion-Tr 48/12-9 (110 W)	Orion-Tr 48/24-5 (120 W)	Orion-Tr 48/48-2,5 (120 W)
Input voltage range (1)	8-17 V	8-17 V	16-35 V	16-35 V	16-35 V	32-70 V	32-70 V	32-70 V
Under voltage shut down	7 V	7 V	14 V	14 V	14 V	28 V	28 V	28 V
Under voltage restart	7,5 V	7,5 V	15 V	15 V	15 V	30 V	30 V	30 V
Nominal output voltage	12.2 V	24.2 V	12.2 V	24.2 V	48.2 V	12.2 V	24.2 V	48.2 V
Output voltage adjust range	10-15 V	20-30 V	10-15 V	20-30 V	40-60 V	10-15 V	20-30 V	40-60 V
Output voltage tolerance	+/- 0.2 V							
Output noise	2mV rms							
Cont. output current at nominal output voltage and 25 °C	9 A	5 A	9 A	5 A	2.5 A	9 A	5 A	2.5 A
Maximum output current (10 s) at nominal output voltage	12.5 A	6.3 A	12.5 A	6.3 A	3.0 A	12.5 A	6.3 A	3.0 A
Short circuit output current	32 A	23 A	39 A	30 A	19 A	27 A	25 A	17 A
Cont. output power at 25 °C	110 W	120 W	110 W	120 W	120 W	110 W	120 W	120 W
Cont. output power at 40 °C	85 W	110 W	85 W	115 W	115 W	85 W	100 W	85 W
Efficiency	87 %	88 %	85 %	87 %	88 %	87 %	86 %	89 %
No load input current	< 50 mA	< 80 mA	< 40 mA	< 60 mA	< 120 mA	< 50 mA	< 60 mA	< 80 mA
Galvanic isolation	200 V dc between input, output and case							
Operating temperature range	-20 to +55 °C (derate 3 % per °C above 40 °C)							
Humidity	Max. 95 % non-condensing							
DC connection	Screw terminals							
Maximum cable cross-section	6 mm ² AWG10							
Weight	0,42 kg (1 lb)							
Dimensions h x w x d	100 x 113 x 47 mm (4.0 x 4.5 x 1.9 inch)							
Standards: Safety Emission Immunity Automotive Directive	EN 60950 EN 61000-6-3, EN 55014-1 EN 61000-6-2, EN 61000-6-1, EN 55014-2 ECE R10-5							

1) If set to nominal or lower than nominal, the output voltage will remain stable within the specified input voltage range (buck-boost function). If the output voltage is set higher than nominal by a certain percentage, the minimum input voltage at which the output voltage remains stable (does not decrease) increases by the same percentage.

See page two for 250 W and 400 W models

Isolated converters 220 - 280 Watt	Orion-Tr 12/12-18 (220 W)	Orion-Tr 12/24-10 (240 W)	Orion-Tr 24/12-20 (240 W)	Orion-Tr 24/24-12 (280 W)	Orion-Tr 24/48-6 (280 W)	Orion-Tr 48/12-20 (240 W)	Orion-Tr 48/24-12 (280 W)	Orion-Tr 48/48-6 (280 W)
Input voltage range (1)	8-17 V	8-17 V	16-35 V	16-35 V	16-35 V	32-70 V	32-70 V	32-70 V
Under voltage shut down	7 V	7 V	14 V	14 V	14 V	28 V	28 V	28 V
Under voltage restart	7,5 V	7,5 V	15 V	15 V	15 V	30 V	30 V	30 V
Nominal output voltage	12.2 V	24.2 V	12.2 V	24.2 V	48.2 V	12.2 V	24.2 V	48.2 V
Output voltage adjust range	10-15 V	20-30 V	10-15 V	20-30 V	40-60 V	10-15 V	20-30 V	40-60 V
Output voltage tolerance	+/- 0,2V							
Output noise	2 mV rms							
Cont. output current at nominal output voltage and 40 °C	18 A	10 A	20 A	12 A	6 A	20 A	12 A	6 A
Maximum output current (10 s) at nominal output voltage	25 A	15 A	25 A	15 A	8 A	25 A	15 A	8 A
Short circuit output current	40 A	25 A	50 A	30 A	25 A	50 A	30 A	25 A
Cont. output power at 25 °C	280 W	280 W	300 W	320 W	320 W	280 W	320 W	320 W
Cont. output power at 40 °C	220 W	240 W	240 W	280 W	280 W	240 W	280 W	280 W
Efficiency	87 %	88 %	88 %	89 %	89 %	87 %	89 %	89 %
Off load current	< 80 mA	< 100 mA	< 100 mA	< 80 mA	< 120 mA	< 80 mA	< 80 mA	< 80 mA
Galvanic isolation	200 VDC between input, output and case							
Operating temperature range	-20 to +55 °C (derate 3 % per °C above 40 °C)							
Humidity	Max. 95 % non-condensing							
DC connection	Screw terminals							
Maximum cable cross-section	16 mm ² AWG6							
Weight	1,3 kg (3 lb)							
Dimensions hwxwd	130 x 186 x 70 mm (5.1 x 7.3 x 2.8 inch)							
Standards: Safety Emission Immunity Automotive Directive	EN 60950 EN 61000-6-3, EN 55014-1 EN 61000-6-2, EN 61000-6-1, EN 55014-2 ECE R10-5							

Isolated converters 360 - 400 Watt	Orion-Tr 12/12-30 (360 W)	Orion-Tr 12/24-15 (360 W)	Orion-Tr 24/12-30 (360 W)	Orion-Tr 24/24-17 (400 W)	Orion-Tr 24/48-8,5 (400 W)	Orion-Tr 48/12-30 (360 W)	Orion-Tr 48/24-16 (380 W)	Orion-Tr 48/48-8 (380 W)
Input voltage range (1)	10-17 V	10-17 V	20-35 V	20-35 V	20-35 V	40-70 V	40-70 V	40-70 V
Under voltage shut down	7 V	7 V	14 V	14 V	14 V	28 V	28 V	28 V
Under voltage restart	7,5 V	7,5 V	15 V	15 V	15 V	30 V	30 V	30 V
Nominal output voltage	12.2 V	24.2 V	12.2 V	24.2 V	48.2 V	12.2 V	24.2 V	48.2 V
Output voltage adjust range	10-15 V	20-30 V	10-15 V	20-30 V	40-60 V	10-15 V	20-30 V	40-60 V
Output voltage tolerance	+/- 0,2V							
Output noise	2 mV rms							
Cont. output current at nominal output voltage and 40°C	30 A	15 A	30 A	17 A	8,5 A	30 A	16 A	8 A
Maximum output current (10 s) at nominal output voltage minus 20%	40 A	25 A	45 A	25 A	15 A	40 A	25 A	15 A
Short circuit output current	60 A	40 A	60 A	40 A	25 A	60 A	40 A	25 A
Cont. output power at 25°C	430 W	430 W	430 W	480 W	480 W	430 W	430 W	430 W
Cont. output power at 40°C	360 W	360 W	360 W	400 W	400 W	360 W	380 W	380 W
Efficiency	87 %	88 %	88 %	89 %	89 %	87 %	89 %	89 %
Off load current	< 80 mA	< 100 mA	< 100 mA	< 80 mA	< 120 mA	< 80 mA	< 80 mA	< 80 mA
Galvanic isolation	200 VDC between input, output and case							
Operating temperature range	-20 to +55 °C (derate 3 % per °C above 40 °C)							
Humidity	Max. 95 % non-condensing							
DC connection	Screw terminals							
Maximum cable cross-section	16 mm ² (AWG6)							
Weight	12 V input and/or 12 V output models: 1.8 kg (3 lb). Other models: 1,6 kg (3.5 lb)							
Dimensions hwxwd	12 V input and/or 12 V output models: 130 x 186 x 80 mm (5.1 x 7.3 x 3.2 inch) Other models: 130 x 186 x 70 mm (5.1 x 7.3 x 2.8 inch)							
Standards: Safety Emission Immunity Automotive Directive	EN 60950 EN 61000-6-3, EN 55014-1 EN 61000-6-2, EN 61000-6-1, EN 55014-2 ECE R10-5							

1) If set to nominal or lower than nominal, the output voltage will remain stable within the specified input voltage range (buck-boost function).
If the output voltage is set higher than nominal by a certain percentage, the minimum input voltage at which the output voltage remains stable (does not decrease) increases by the same percentage.